

- 10.4" TFT Colour Touchscreen
- 65,535 Colours, VGA (640 x 480)
- MicroSD™ Data storage upto 32GB
- Real Time Clock
- 2 CAN Port, 3 RS-232 / RS-485
- 2 Integral Ethernet Ports
- USB Port for Programming
- USB Port for Flash Drives upto 2TB
- Addressable function keys
- 1MB RAM (Program), 27MB (Graphical)
- IP65 (NEMA4)
- 10 - 30 VDC Power Supply
- Online Programming
- Free Configuration Software
- Remote I/O Communication
- Optional - Modem (SMS, GSM, GPRS)



Options & Ordering Codes

Standard Options	DI	DO	AI	AO
i3DX12Z/10D03-SEHF	12	6 Relay	4	-
i3DX12Z/13C14-SEHF	12	12	2*	2
i3DX12C/20B05-SEHF	24	16	2	-
i3DX12Z/10B04-SEHF	12	12	2	-
i3DX12Z/10E24-SEHF	12	12	6*	4
i3DX12Z/00000-SEHF	-	-	-	-

* Universal Analogue Inputs

i3	DX	12	Z	/	10	D	0	3	-	S	E	H	F
Colour Display								Digital Outputs					
640 x 480				DX				0	No Digital Output				
Comms Ports								3	6 (Relay)				
RS-232, RS-485, RS-232/485				12				4	12 (DC)				
Programmable Keys								5	16 (DC)				
7 Programmable Keys				Z				Analogue Outputs		Serial	2 x Ethernet and 2 x CAN port		MicroSD™ Flash Card
Digital Inputs							0	No Analogue Output					
No Digital Input					00		1	2 (12 Bit)					
12 Digital Inputs					10		2	4 (12 Bit)					
24 Digital Inputs					20		Analogue Inputs			iCAN	H		
12 Digital Inputs + Temperature PT100/TC					13	0	No Analogue Input			CANopen	A		
						B	2 (12 Bit)			Devicenet	D		
						C	2 (14 Bit)			J1939	J		
						D	4 (12 Bit)						
						E	6 (14/17 Bit)						

i³DX Intelligent Control Station

Technical Specifications

General Specifications	
Required Power (Steady State)	650mA @ 24VDC
Required Power (Inrush)	25A for <1ms @ 24VDC DC Switched
Primary Voltage Range	10-30VDC
Relative Humidity	5 to 95% Non-Condensing
Clock Accuracy	+/-20ppm Maximum at 25°C (+/-1 Minute per month)
Operating Temperature	-10°C to +60°C
Storage Temperature	-40°C to +60°C
Weight	1.82kg (without I/O)
Approvals	cUL, UL, CE


Display Specifications	
Display Type	10.4" VGA TFT
Resolution	640 x 480
Colour	16-bit (65,536)
Screen Memory	27MB
User-Programmable Screens	1023
Backlight	LED - 50,000 hour life
Screen Update Rate	User configurable within the scan time (perceived as instantaneous in many cases)

Control & Logic Specifications	
Control Language Support	Advanced Ladder Logic Full IEC 61131-3
Logic Program Size & Logic Scan Rate	1MB Maximum 0.013ms/k
Online Programming Changes	Supported in Advanced Ladder
I/O Support	Digital Inputs - 2048
	Digital Outputs - 2048
	Analogue Inputs - 512
	Analogue Outputs - 512
General Purpose Registers	50,000 (words) Retentive 16,384 (bits) Retentive 16,384 (bits) Non-retentive

Connectivity	
Serial Ports	1 RS-232 & 1 RS-485 on first modular jack (MJ1/2) 1 RS-232 or 1 RS-485 on second modular jack (MJ3)
USB mini-B	USB 2.0 (480MHz) Programming & Data Access
USB A	USB 2.0 (480MHz) for USB FLASH Drives (up to 2TB)
CAN	Remote I/O, Peer-to-Peer Comms, i3 Configurator
Ethernet	10/100MB (Auto-MDX), Modbus TCP, HTTP, FTP, SMTP, i3 Configurator, Ethernet IP
Remote I/O	IOS, Smart I/O, iSmart
Removable Memory	MicroSD™ (support for 32GB max) Application updates, Datalogging, more


Input / Output Specifications										
Model	DC In	DC Out	Relays	HS In	HS Out	mA/V In	mA/V RTD/TC	mA/V Out	High Speed Counters	
10D03	12		6	4		4			Number of Counters	2
10B04	12	12		4	2	2			Maximum Frequency	500kHz each
20B05	24	16		4	2	2			Accumulator Size	32-bits each
13C14	12	12		4	2		2	2	Modes Supported	
10E24	12	12		4	2		6*	4*	Totalizer	Quadrature
There are 4 high-speed inputs of the total DC inputs. There are 2 high-speed outputs of the total DC outputs. Model 10D03, 10B04, 20B05 feature 12-bit analogue I/O. Model 13C14 features 14/16-bit analogue I/O. High-speed outputs can be used for PWM and Pulse Train Outputs, currently limited to <65kHz. Model 10E14 features a 14/17 bit analogue I/O.									Pulse Measurement	Frequency Measurement
									2 Position Controlled Outputs 1 ON/OFF Setpoint per Output	
*Up to six mA/V In, RTD/TC, and mA/V Out										

Dimensions & Panel Cutout



i³DX Intelligent Control Station

Ports & Connectors



DC Input / Frame

Torque rating: 4.5-7 Lb-in
(0.50-0.78Nm)

DC- is internally connected to I/O V-,
but is isolated from CAN V-

A Class 2 power supply must be used




CAN

Locking Spring-Clamp
2-Terminators Per Conductor
Mounting screw torque rating: 4.5 Lb-in
(0.50Nm)

SHLD and V+ pins are not
internally connected to i³DX

Primary Power Port Pins		
Pin	Signal	Signal Description
1	Ground	Frame Ground
2	DC-	Input Power Supply Ground
3	DC+	Input Power Supply Voltage




MJ1/2 Independent Serial Ports

MJ1: RS-232 with Full Handshaking

MJ2: RS-485 Half-Duplex

PIN	MJ1 PINS		MJ2 PINS	
	Signal	Direction	Signal	Direction
8	TXD	OUT	-	-
7	RXD	IN	-	-
6	0 V	Ground	0 V	Ground
5	+5V@60mA	OUT	+5V@60mA	OUT
4	RTS	OUT	-	-
3	CTS	IN	-	-
2	-	-	RX- / TX-	IN / OUT
1	-	-	RX+ / TX+	IN / OUT




MJ3 Serial Port

Two multiplexed serial ports on one
modular jack (8posn)

PIN	MJ3 PINS	
	Signal	Direction
8	TXD RS-232	OUT
7	RXD RS-232	IN
6	0 V	Ground
5	+5V@60mA	OUT
4	TX- RS-485	OUT
3	TX+ RS-485	OUT
2	RX- RS-485	IN
1	RX+ RS-485	IN

DIP Switches



Switch	Name	Function	Default
1	MJ3 RS-485 Termination	ON = Terminated	OFF
2	MJ3 Duplex	ON = Half	OFF
3		OFF = Full	
4	MJ2 RS-485 Termination	ON = Terminated	OFF

Fixed Address	Digital/Analog I/O Function	i3DX Model				
		10D03	10B04	20B05	13C14	10E24
%I1	Digital Inputs	1-12	1-12	1-24	1-12	1-12
	Reserved	13-32	13-31	25-31	13-31	13-31
	ESCP Alarm	n/a	32	32	32	32
%Q1	Digital Outputs	1-6	1-12	1-16	1-12	1-12
	Reserved	7-24	13-24	17-24	13-24	13-24
%AI1	Analogue Inputs	1-4	1-2	1-2	1-2	1-4:33-38
	Reserved	5-12	3-12	3-12	3-12	n/a
%AQ1	Reserved	n/a	1-8	1-8	1-8	1-12
	Analogue Outputs	n/a	n/a	n/a	9-10	n/a

Reserved areas maintain backward compatibility with other i3 Controller models

Built-in I/O

I/O is mapped into i3 Register space, in three separate areas – Digital/Analogue I/O, High-Speed Counter I/O, and High-Speed Output I/O. Digital/Analogue I/O location is fixed starting at 1, but the High-Speed Counter and High-Speed Output references may be mapped to any open register location. For more details on using the High-Speed Counter and High-Speed Outputs, see the i3DX User's Manual.

Default Address*	High Speed Counter Function	i3DX Models
%I1601	Status Bits	1-8
&Q1601	Command Bits	1-32
%AI0401	Accumulator 1&2	1-8
%AQ0401	Preload & Match Values	1-12

*Starting Address locations for
%, %Q, %AI & %AQ may
be re-mapped by user

Default Address*	High Speed Output Function	i3DX Models
%I1617	Status Bits	1-8
&Q**	Command Bits	1-32
n/a	n/a	n/a
%AQ0421	PWM or Pulse Train Parameters	1-20

*Starting Address locations for
%I & %AQ may be re-mapped by user


**Q1-Q2 are part of the Fixed I/O Map. In High
Speed Output mode they can be used to initiate a
Stepper/PTO Move

i³DX Intelligent Control Station


10D03 I/O Board Specifications

Digital DC Inputs			Digital Relay Outputs			
Inputs per Module		12 including 4 configurable HSC inputs	Outputs per Module		6 Relay	
Commons per Module		1	Commons per Module		6	
Input Voltage Range		10-30 VDC	Max. Switching Current per Relay		3A @ 250 VAC, Resistive	
Absolute Max. Voltage		35 VDC Max	Max. Total Output Current		5A Continuous	
Input Impedance		10 kΩ	Max. Switching Voltage		275 VAC, 30 VDC	
Input Current	<u>Positive Logic</u>	<u>Negative Logic</u>	Max. Switched Power			1250 VAC, 150W
Upper Threshold	0.8mA	-1.6mA				
Lower Threshold	0.3mA	-2.1mA				
Max. Upper Threshold		8 VDC	Contact Isolation to Ground		1000 VAC	
Max. Lower Threshold		3 VDC	Max. Voltage Drop at Rated Current		0.5V	
OFF to ON Response		1 ms	Expected Life (see below for detail)		No Load: 5,000,000 200,000 at rated load	
ON to OFF Response		1 ms	Max. Switching Rate		300 CPM at no load 20 CPM at rated load	
HSC Max. Switching Rate		10 kHz Totalizer/Pulse, Edges 5 kHz Frequency/Pulse, Width 2.5 kHz Quadrature	Type		Mechanical Contact	
			Response Time		One update per ladder scan plus 10ms	
Analogue Inputs, Medium Resolution						
Number of Channels		4	Input Ranges		0-10 VDC, 0-20 mA, 4-20 mA	
Safe Input Voltage Range		-0.5V to 12V	Input Impedance (clamped @ -0.5VDC to 12VDC)		Current Mode: 100 Ω Voltage Mode: 500 kΩ	
Nominal Resolution		12 Bits	%AI Full Scale		32,000	
Max. Over Current		35 mA	Conversion Speed		Once per Ladder Scan	
Max. Error at 25°C (excluding zero)		4-20 mA 1.00% of FS 0-20 mA 1.00% of FS	Filtering			160 Hz hash (noise) filter 1-128 scan digital running average filter
Adjusting filtering may tighten		0-10 VDC 1.50% of FS				

J1 (Orange)	Name
I1	IN1
I2	IN2
I3	IN3
I4	IN4
I5	IN5
I6	IN6
I7	IN7
I8	IN8
H1	HSC1 / IN9
0V	Common
A1	Analogue IN1
A2	Analogue IN2
A3	Analogue IN3
A4	Analogue IN4
0V	Common



J2 (Black)	Name
C6	Relay 6 COM
R6	Relay 6 NO
C5	Relay 5 COM
R5	Relay 5 NO
C4	Relay 4 COM
R4	Relay 4 NO
C3	Relay 3 COM
R3	Relay 3 NO
C2	Relay 2 COM
R2	Relay 2 NO
C1	Relay 1 COM
R1	Relay 1 NO
H4	HSC4 / IN12
H3	HSC3 / IN11
H2	HSC2 / IN10



Model 2 Jumper Setting Details

JP1 Digital DC In / HSC

Positive Logic
Negative Logic

Default
001XLE026

JP2 Analog In (A1 - A4)

Current (20 mA)
Voltage (10 V)


A1
A2
A3
A4

Default

Note: The Module Setup configuration must match the selected I/O (JP) jumper settings

Note: When using JP2 (A1-A4), each channel can be independently configured.

Location of I/O jumpers (JP1 & JP2) and wiring connectors (J1 and J2) with back cover removed.



i³DX Intelligent Control Station

Safety

WARNING: Battery may explode if mistreated. Do not recharge, disassemble or dispose of in fire.

WARNING: EXPLOSION HAZARD - BATTERIES MUST ONLY BE CHANGED IN AN AREA KNOWN TO BE NON-HAZARDOUS

This equipment is suitable for use in Class 1, Division 2, Groups A, B, C and D or Non-hazardous locations only.

FOR U.S. & CANADA ONLY

Power input and output (I/O) wiring must be in accordance with Class 1, Division 2 wiring methods of the National Electric Code, NFPA70 for installations in the U.S. or as specified in Section 18-1J2 of the Canadian Electric Code for installations within Canada and in accordance with the authority having jurisdiction.

WARNING: EXPLOSION HAZARD - Do not disconnect equipment unless power has been switched off or the area is known to be non-hazardous.

WARNING: EXPLOSION HAZARD - Substitution of components may impair suitability for Class 1, Division 2.

Digital outputs shall be supplied from the same source as the i3 Controller.

WARNING: Only qualified electrical personnel familiar with the construction and operation of this equipment and the hazards involved should install, adjust, operate, or service this equipment. Read and understand this manual and other applicable manuals in their entirety before proceeding. Failure to observe this precaution could result in severe bodily injury or loss of life.

WARNING: To avoid the risk of electric shock or burns, always connects the earth ground before making any other connections.

WARNING: To reduce the risk of fire, electrical shock, or physical injury it is strongly recommended to fuse all Power Sources connected to the i3 controller. Be sure to locate fuses as close to the source as possible.

WARNING: Replace fuse with the same type and rating to provide protection against risk of fire and shock hazards.

WARNING: In the event of repeated failure, do not replace the fuse again as a repeated failure indicates a defective condition that will not clear by replacing the fuse.

Jumpers on connector JP1 and others shall not be removed or replaced while the circuit is live unless the area is known to be free of ignitable concentrations of flammable gases or vapours.

Common Cause of Analogue Input Tranzorb Failure

If a 4-20mA circuit is initially wired with loop power, but without a load, the analogue Input could see 24VDC. This is higher than the rating of the tranzorb. This can be solved by NOT connecting loop power prior to load connection, or by installing a low-cost PTC in series between the load and analogue input.

