

# i<sup>3</sup>C Mini Intelligent Control Station

- 3.5" TFT Colour Touchscreen
- 65,535 Colours, QVGA (320 x 240)
- MicroSD™ Data storage upto 32GB
- Real Time Clock
- 1 CAN Port, 1 RS-232, 1 RS-485
- 1 Integral Ethernet Port
- USB Port for Programming
- USB Port for Flash Drives upto 2TB
- Addressable function keys
- 1MB RAM (Program), 27MB (Graphical)
- IP65 (NEMA4)
- 10 - 30 VDC Power Supply
- Online Programming
- Free Configuration Software
- Remote I/O Communication
- Optional - Modem (SMS, GSM, GPRS)



## Options & Ordering Codes

Standard Options	DI	DO	AI	AO
i3CM12Y/10D03-SEHF	12	6 Relay	4	-
i3CM12Y/13C14-SEHF	12	12	2*	2
i3CM12Y/20B05-SEHF	24	16	2	-
i3CM12Y/10B04-SEHF	12	12	2	-
i3CM12Y/10E24-SEHF	12	12	6*	4
i3CM12Y/00000-SEHF	-	-	-	-

\* Universal Analogue Inputs

i3	CM	12	Y	/	10	D	0	3	-	S	E	H	F		
<b>Colour Display</b>															
320 x 240		<b>CM</b>													
<b>Comms Ports</b>															
RS-232, RS-485		<b>12</b>													
<b>Programmable Keys</b>															
4 Programmable Keys		<b>Y</b>													
<b>Digital Inputs</b>															
No Digital Input						<b>00</b>									
12 Digital Inputs						<b>10</b>									
24 Digital Inputs						<b>20</b>									
12 Digital Inputs + Temperature PT100/TC						<b>13</b>									
								<b>Digital Outputs</b>							
								0		No Digital Output					
								3		6 (Relay)					
								4		12 (DC)					
								5		16 (DC)					
								<b>Analogue Outputs</b>							
								0		No Analogue Output					
								1		2 (12 Bit)					
								2		4 (12 Bit)					
								<b>Analogue Inputs</b>							
								0		No Analogue Input					
								B		2 (12 Bit)					
								C		2 (14 Bit)					
								D		4 (12 Bit)					
								E		6 (14/17 Bit)					
										Serial		In-built Ethernet and CAN port		MicroSD™ Flash Card	
										iCAN		<b>H</b>			
										CANopen		<b>A</b>			
										Devicenet		<b>D</b>			
										J1939		<b>J</b>			

# i<sup>3</sup>C Mini Intelligent Control Station

## Technical Specifications

General Specifications	
Required Power (Steady State)	190mA @ 12VDC / 95mA @ 24VDC
Required Power (Inrush)	2A for <1ms @ 24VDC DC Switched
Primary Voltage Range	10-30VDC
Relative Humidity	5 to 95% Non-Condensing
Clock Accuracy	+/-20ppm Maximum at 25°C (+/-1 Minute per month)
Operating Air Temperature	-10°C to +60°C
Storage Temperature	-30°C to +70°C
Weight	0.34kg (without I/O)
Approvals	cUL, UL, CE


Control & Logic Specifications	
Control Language Support	Advanced Ladder Logic Full IEC 61131-3
Logic Program Size & Logic Scan Rate	1MB Maximum 0.013ms/k
Online Programming Changes	Supported in Advanced Ladder
I/O Support	Digital Inputs - 2048
	Digital Outputs - 2048
	Analogue Inputs - 512
	Analogue Outputs - 512
General Purpose Registers	50,000 (words) Retentive 16,384 (bits) Retentive 16,384 (bits) Non-retentive

Display Specifications	
Display Type	3.5" QVGA TFT
Resolution	320 x 240
Colour	16-bit (65,536)
Screen Memory	27MB
User-Programmable Screens	1023
Backlight	LED - 50,000 hour life
Screen Update Rate	User configurable within the scan time (perceived as instantaneous in many cases)

Connectivity	
Serial Ports	1 RS-232 & 1 RS-485 on first modular jack (MJ1/2)
USB mini-B	USB 2.0 (480MHz) Programming & Data Access
USB A	USB 2.0 (480MHz) for USB FLASH Drives (up to 2TB)
CAN	Remote I/O, Peer-to-Peer Comms, i3 Configurator
Ethernet	10/100MB (Auto-MDX), Modbus TCP, HTTP, FTP, SMTP, i3 Configurator, Ethernet IP
Remote I/O	IOS, Smart I/O, iSmart
Removable Memory	MicroSD™ (support for 32GB max) Application updates, Datalogging, more


Input / Output Specifications											
Model	DC In	DC Out	Relays	HS In	HS Out	mA/V In	mA/V RTD/TC	mA/V Out	High Speed Counters		
10D03	12		6	4		4			Number of Counters	2	
10B04	12	12		4	2	2			Maximum Frequency	500kHz each	
20B05	24	16		4	2	2			Accumulator Size	32-bits each	
13C14	12	12		4	2		2	2	Modes Supported		
10E24	12	12		4	2		6*	4*	Totalizer	Quadrature	
There are 4 high-speed inputs of the total DC inputs. There are 2 high-speed outputs of the total DC outputs. Model 10D03, 10B04, 20B05 feature 12-bit Analogue I/O. Model 13C14 features 14/16-bit Analogue I/O. High-speed outputs can be used for PWM and Pulse Train Outputs, currently limited to <65kHz. Model 10E14 features a 14/17 bit Analogue I/O.										Pulse Measurement	Frequency Measurement
*Up to six mA/V In, RTD/TC, and mA/V Out										2 Position Controlled Outputs 1 ON/OFF Setpoint per Output	

## Dimensions & Panel Cutout



# i<sup>3</sup>C Mini Intelligent Control Station

## Ports & Connectors



### DC Input / Frame

Torque rating: 4.5-7 Lb-in  
(0.50-0.78Nm)  
DC- is internally connected to I/O V-,  
but is isolated from CAN V-  
A Class 2 power supply must be used




### CAN

Locking Spring-Clamp  
2-Terminators Per Conductor  
Mounting screw torque rating: 4.5 Lb-in  
(0.50Nm)  
SHLD and V+ pins are not  
internally connected to i<sup>3</sup>C Mini

Primary Power Port Pins		
Pin	Signal	Signal Description
1	Ground	Frame Ground
2	DC-	Input Power Supply Ground
3	DC+	Input Power Supply Voltage

Primary Power Port Pins			
Pin	Signal	Description	Direction
1	V-	CAN Ground - Black	-
2	CN L	CAN Data Low - Blue	IN / OUT
3	SHLD	Shield Ground - None	-
4	CN H	CAN Data High - White	IN / OUT
5	V+ (NC)	No Connect - Red	-




### MJ1/2 Independent Serial Ports

MJ1: RS-232 with Full Handshaking  
MJ2: RS-485 Half-Duplex

PIN	MJ1 PINS		MJ2 PINS	
	Signal	Direction	Signal	Direction
8	TXD	OUT	-	-
7	RXD	IN	-	-
6	0 V	Ground	0 V	Ground
5	+5V@60mA	OUT	+5V@60mA	OUT
4	RTS	OUT	-	-
3	CTS	IN	-	-
2	-	-	RX- / TX-	IN / OUT
1	-	-	RX+ / TX+	IN / OUT

### DIP Switches



Switch	Name	Function	Default
1	RS-485 Termination	ON = Terminated	OFF
2	Spare	Always Off	OFF
3	Factory Use	Always Off	OFF

### Built-in I/O

I/O is mapped into i<sup>3</sup>C Register space, in three separate areas – Digital/Analogue I/O, High-Speed Counter I/O, and High-Speed Output I/O. Digital/Analogue I/O location is fixed starting at 1, but the High-Speed Counter and High-Speed Output references may be mapped to any open register location. For more details on using the High-Speed Counter and High-Speed Outputs, see the i<sup>3</sup>C Mini User's Manual.

Fixed Address	Digital/Analogue I/O Function	i <sup>3</sup> C Mini Model				
		10D03	10B04	20B05	13C14	10E24
%I1	Digital Inputs	1-12	1-12	1-24	1-12	1-12
	Reserved	13-32	13-31	25-31	13-31	13-31
	ESCP Alarm	n/a	32	32	32	32
%Q1	Digital Outputs	1-6	1-12	1-16	1-12	1-12
	Reserved	7-24	13-24	17-24	13-24	13-24
%AI1	Analogue Inputs	1-4	1-2	1-2	1-2	1-4:33-38
	Reserved	5-12	3-12	3-12	3-12	n/a
%AQ1	Reserved	n/a	1-8	1-8	1-8	1-12
	Analogue Outputs	n/a	n/a	n/a	9-10	n/a

Reserved areas maintain backward compatibility with other i<sup>3</sup>C Controller models

Default Address*	High Speed Counter Function	i <sup>3</sup> C Mini Models
%I1601	Status Bits	1-8
&Q1601	Command Bits	1-32
%AI0401	Accumulator 1&2	1-8
%AQ0401	Preload & Match Values	1-12

\*Starting Address locations for %I, %Q, %AI & %AQ may be re-mapped by user

Default Address*	High Speed Output Function	i <sup>3</sup> C Mini Models
%I1617	Status Bits	1-8
&Q**	Command Bits	1-32
n/a	n/a	n/a
%AQ0421	PWM or Pulse Train Parameters	1-20

\*Starting Address locations for %I & %AQ may be re-mapped by user

\*\*Q1-Q2 are part of the Fixed I/O Map. In High Speed Output mode they can be used to initiate a Stepper/PTO Move

# i<sup>3</sup>C Mini Intelligent Control Station

## Safety

**WARNING:** Battery may explode if mistreated. Do not recharge, disassemble or dispose of in fire.

**WARNING: EXPLOSION HAZARD - BATTERIES MUST ONLY BE CHANGED IN AN AREA KNOWN TO BE NON-HAZARDOUS**

This equipment is suitable for use in Class 1, Division 2, Groups A, B, C and D or Non-hazardous locations only.

**FOR U.S. & CANADA ONLY**

Power input and output (I/O) wiring must be in accordance with Class 1, Division 2 wiring methods of the National Electric Code, NFPA70 for installations in the U.S. or as specified in Section 18-1J2 of the Canadian Electric Code for installations within Canada and in accordance with the authority having jurisdiction.

**WARNING: EXPLOSION HAZARD - Do not disconnect equipment unless power has been switched off or the area is known to be non-hazardous.**

**WARNING: EXPLOSION HAZARD - Substitution of components may impair suitability for Class 1, Division 2.**

Digital outputs shall be supplied from the same source as the i3 Controller.

**WARNING:** Only qualified electrical personnel familiar with the construction and operation of this equipment and the hazards involved should install, adjust, operate, or service this equipment. Read and understand this manual and other applicable manuals in their entirety before proceeding. Failure to observe this precaution could result in severe bodily injury or loss of life.

**WARNING:** To avoid the risk of electric shock or burns, always connects the earth ground before making any other connections.

**WARNING:** To reduce the risk of fire, electrical shock, or physical injury it is strongly recommended to fuse all Power Sources connected to the i3 controller. Be sure to locate fuses as close to the source as possible.

**WARNING:** Replace fuse with the same type and rating to provide protection against risk of fire and shock hazards.

**WARNING:** In the event of repeated failure, do not replace the fuse again as a repeated failure indicates a defective condition that will not clear by replacing the fuse.

Jumpers on connector JP1 and others shall not be removed or replaced while the circuit is live unless the area is known to be free of ignitable concentrations of flammable gases or vapours.

## Common Cause of Analogue Input Tranzorb Failure

If a 4-20mA circuit is initially wired with loop power, but without a load, the analogue input could see 24VDC. This is higher than the rating of the tranzorb. This can be solved by NOT connecting loop power prior to load connection, or by installing a low-cost PTC in series between the load and analogue input.

